

Figure 1: EL-2614

The EL-2614 is a keyfob transmitter designed for use with Electronics Line 3000's supervised wireless range of receivers.

## Registration

To register the EL-2614:

1. Set the receiver to Registration mode.
2. Press one of the buttons, making sure that the LED lights up when the button is pressed.
3. Press the same button again to complete the registration process.

**Note: Alternatively, the EL-2614 can be registered to the receiver by manually entering the transmitter's serial number.**

## Battery Replacement

If the LED blinks during transmissions, this indicates that the batteries are low and need replacing.

To replace the batteries:

1. Insert a small screwdriver into the pry-off slot – see Figure 2. Carefully twist the screwdriver to separate the front and back of the casing.
2. Observing correct polarity, replace the batteries.
3. Close the casing making sure that the front and back click shut.




Figure 2: Opening the Casing

## Technical Specifications

Antenna: Built-in whip

Frequency: 868.35, 433.92 or 418MHz FM

Power: 2 x 3V Lithium Battery, Size CR1225

Current Consumption:

16mA (transmission),

2µA (standby)

RFI Immunity: 40V/m

Operating Temperature: 0 - 60°C

Dimensions: 62 x 42 x 15mm




Figure 3: EL-2614  
Rear View (Casing Open)



Electronics Line

Electronics Line 3000 Ltd.: 2 Granit Street, Kiryat Arieh, POB 3253, Petah Tikvah 49130 Israel. Tel: (972-3) 918-1333, Fax: (972-3) 922-0831

USA: 5637 Arapahoe Avenue, Boulder, Colorado 80303. Tel: (800) 683-6835, Fax: (303) 938-8062

UK: Unit 7, Levis Trading Estate, Station Road, Stechford, Birmingham B33 9AE. Tel: (44-121) 789-8111, Fax: (44-121) 789-8055

France: ZI-61, rue du Marché Rollay, 94500 Champigny-Sur-Marne. Tel: (33-1) 45.16.19.20, Fax: (33-1) 45.16.19.29

All data is subject to change without prior notice. In no event shall Electronics Line 3000 Ltd. (EL3K) be liable for an amount in excess of EL3K's original selling price of this product, for any loss or damage whether direct, indirect, incidental, consequential or otherwise arising out of any failure of the product. Hereby, Electronics Line 3000 Ltd. declares that this transmitter is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC. 868.35MHz frequency transmitters are not intended for use in Bulgaria, Greece, Poland and Slovenia.



ZIO239B (6/03)